

# 802R/802BT



quantumdata

## VIDEO TEST INSTRUMENTS

Generate video signals associated with the design, manufacture and service of computer, consumer, medical, military and other video products.

802BT/R provides single link HDMI 1.1 (shown) and single link DVI out the HDMI connector. Alternatively the 802BT can be equipped with single link DVI and the 802R can be equipped with dual link DVI.

## KEY FEATURES + BENEFITS

### Management

Update and configure all networked instruments through a graphical management program (VGM) from your computer.

### HDMI with DVI support

Single link (up to 165 MHz) HDMI with single link DVI out same connector.

### DVI

Dual link DVI up to 330MHz (802R only)  
Single link DVI up to 165MHz (802BT/R)

### LVDS

Open LDI/FPD-link to 32.5-112/170MHz.

### HDCP

Production test keys included with HDMI and DVI signals. Now supports full Dual link DVI HDCP.

### Comprehensive timing + patterns

Include extensive library of standard timings and patterns. Add your own custom timings and patterns.



<b>HDCP</b>		
HDMI and DVI	Authentication and encryption of uncompressed HDMI and DVI signals	
<b>HDMI InfoFrames</b>		
HDMI	Verify InfoFrames sent to display	
<b>HDMI Pixel Repetition</b>		
HDMI	Test gaming formats with variable horizontal resolution	
<b>HDMI Active Format Descriptor (AFD)</b>		
HDMI	Verify HDMI content mapping	
<b>HDMI Audio Tests</b>		
Rate	Vary audio sampling rate to test sink handling	
Frequency	Vary audio frequency to test sink handling	
Amplitude	Vary audio amplitude to test sink handling	
<b>EDID Read</b>		
HDMI, DVI, VGA	Auto-configuration of generator format list	
Data channels		
Physical	I2C per VESA E-DDC	
Protocols	DDC2B, E-DDC & DDC/CI (reads E-EDID Ver 1.3)	
<b>EDID Testing</b>		
HDMI, DVI, VGA	Reads EDID from display and presents as displayed image	
<b>EDID Compliance Testing</b>		
HDMI	HDMI EDID processing	
<b>DV Swing Test</b>		
HDMI, DVI	Vary TMDS digital video signal swing in 4mV increments from 150 to 1560 mVp-p (programmable)	
<b>Scrolling Image Test</b>		
All interfaces	Scroll any static image	
<b>Special Sync Tool</b>		
Analog video	Trigger scope or inspection camera anywhere in video	
<b>Formats and Images</b>		
Standard formats	Over 200 formats for testing IT, CE, military and other display test applications	
Custom formats	VGM with graphical format editor	
<b>Patterns</b>		
Pattern file types	BMP downloads through USB	
Standard patterns	Over 200 standard static and dynamic images included for testing CRTs and FPDs	
Custom patterns	VGM with graphical image editor	
Internal data storage	15 MB	
<b>Test Sequences</b>		
	Create test sequences with unlimited number of steps; each step defines a video format, image, sync, gating and duration (0.1 sec to 24 hours, or frames)	
<b>General Specifications</b>		
Size (mm)	311mm W, 95mm H, 203mm D, 2.27kg	
Humidity	30 to 80% RH (non-condensing)	
Operating temp.	0 to 40° C	
AC Mains		
Frequency	47 to 63 Hz	
Voltage	90-264 VAC	

Specifications and features are subject to change without notice. Rev. Q.

<b>HDMI (if selected, DVI and LVDS interface cannot be added)</b>		
Connector	One HDMI Type A	
TMDS	Single (165 MHz)	
Video		
TMDS protocols	DVI 1.0 and HDMI 1.1	
Encoding	RGB or YCbCr (only RGB in DVI mode)	
Sampling modes	4:4:4 or 4:2:2 (only 4:4:4 in DVI mode)	
Clocks per pixel	1 or 2	
Pixel repetition	1 to 10 using interactive test image	
TMDS differential swing	150-1560 mVp-p (programmable)	
Quantization modes	Full w/optional gamma correction	
	ITU-R BT.709-5 Part 1, Sec 6.10	
	SMPTE 296M Sec 7.12	
	under/overshoot	
Colorimetry	Legacy HDTV SMPTE 260M-1999	
	Table 1, ITU-R BT.601-5 Sec 3.5.1	
	and ITU-R BT.709-5 Sec 4.2-1125	
Content fitting methods	All AFD cases (Shoot & Protect, Overscan, Under-scan, Letterbox/Pillarbox, Anamorphic Squeeze)	
Aspect ratio		
Content	4:3, 14:9, 16:9	
Embedded	4:3, 16:9	
Format (coded)	4:3, 16:9	
Format timings	All EIA/CEA-861-B formats	
	All E-EDID sink-requested < 81 MHz	
Data (island) packet	General control packet, audio samples,	
generator types	ACR data, InfoFrames, null frame	
InfoFrame types generated	AVI, SPD, AUD, MPG, GIF (generic)	
Audio		
Streams	4	
Channels	8	
Bits per sample	16, 20, 24	
Sampling rates	32.0, 44.1, 48, 88.2, 96.0, 176.4, 192 kHz	
Stream type	IEC 60958-3 Consumer LPCM (IEC61937 possible with external source)	
Audio content	FL and FR	
Mixer mux	Sinewave or external audio	
Embedded sonic data generator		
Channels	8	
Waveform	Sinewave	
Amplitude	-96.3 to 0.0 dBFS	
Frequency Change	20 Hz to 20 kHz	
Controls	Mute, amplitude, frequency	
External audio interface		
Type	SPDIF input (coaxial)	
Amplitude	As received	
Connector	VGA w/special SPDIF I/O	
Cable	75 ohm special VGA-to-RCA	
<b>DVI (if selected, HDMI and LVDS interface cannot be added)</b>		
Connector	DVI dual link (R only)	
Links	Single link or dual link up to 25-330MHz	
TMDS protocols	DM 1.0	
Encoding	RGB (4:4:4 with 8-bits/component)	
TMDS differential swing	150-1560 mVp-p (programmable)	
<b>LVDS (if selected, HDMI and DVI interface cannot be added)</b>		
Connector	MDR-36	
Pixel Clock Rates	Dual pixel mode: 32.5MHz to 112MHz	
	Single pixel mode: 32.5MHz to 170MHz	
<b>Analog Composite</b>		
Connectors	CVBS (BNC) and S-Video	
Encoding	NTSC and PAL	
Sample rate	24.55-29.50 MHz	
Pixel rate	12.27-14.75 MHz	
Pixel aspect ratio	Standard or square	
Video Swing	700 mV default, adjustable 0 - 1000 mV	
Sync Swing	300 mV default, adjustable 0 - 400 mV	
Calibration	1000 mVp-p fixed w/programmable self-calibration w/ internal reference	

<b>Analog Component</b>	
<b>(included with analog video option)</b>	
Connector	VGA
Color encoding	RGB, YPbPr (unfiltered)
Video levels	
Video swing	0-1000 mV
Sync swing	0-400 mV (bi-level), 0-800 (tri-level)
Video setup	0-100 IRE
Calibration	Self-calibration with internal reference
Protection	Buffered with 75 ohm isolation
Internal data storage	15 MB
<b>Digital Sync</b>	
Outputs	HS, VS and Special Sync
Swing	> 2V fixed into 75 ohm
<b>Pixel Clock</b>	
Frequency range	
Analog component	3.9975-400 MHz (R) - 200Mhz(BT)
HDMI	25-165 MHz (single-link)
DVI	25-165 MHz (single-link)
	25-330 MHz (dual-link)
Step	Less than 0.1 Hz
Accuracy	50 ppm (electronically adjustable to < 5 ppm with external frequency counter)
<b>Horizontal Timing</b>	
Frequency range (kHz)	
Analog component	8-1000
Analog composite	15.734 or 15.625
HDMI / DVI	8-1000
Total pixels (max)	65,535
Active pixels (max)	4096
Blank pixels (min)	
Analog component	0
HDMI	138 (worst case)
DVI	128
Step pixels	
Analog component	1 (2 above 165 MHz)
HDMI	1
DVI	1
<b>Vertical Timing</b>	
Frequency range	
	1-650 Hz
Total lines (max)	4095 progressive, 8193 interlaced and segmented
Active lines (max)	4096
Blank lines (min)	1 to Total-1
Step lines	1
Scan types	Progressive, interfaced, segmented
Composite sync types	ORed, Serrated, Serrated and Equalized, Tri-level
<b>Video Memory</b>	
Configuration	
	4096 x 4096 x 8-bit indexed color
	2048 x 2048 x 24-bit TrueColor
Color depth	
	32 (24-bit TrueColor) up to 100 MHz for 802R-400; up to 82.5MHz for 802BT/R-300
	8 bits up to 200, 300 or 400 MHz
<b>Administration</b>	
Physical user interface (selection knobs and keys with LCD display)	
Control interfaces	RS-232 serial, USB, GPIB
Create custom Microsoft Windows-based applications using Quantum Data SDK (includes API documentation, sample application & source)	
USB port	Download bitmap image files
PCMCIA slot	Backup settings, transfer settings from one generator to another, and store bitmap images for rapid recall using standard SRMA card.